

UTILITY PATENT APPLICATION TRANSMITTAL UNDER 37 C.F.R. §1.53(b)

ASSISTANT COMMISSIONER FOR PATENTS

Box PATENT APPLICATION

Washington D.C. 20231

Case Docket No.:K-164

Sir:

Transmitted herewith for filing is the patent application of

INVENTOR OR APPLICATION IDENTIFIER: Sun Gil KIM and Sung Chul YANG

FOR: DEVICE FOR TRANSMISSION/RECEPTION OF FACSIMILE DATA IN WIRELESS LOCAL LOOP (WLL) SYSTEM

Enclosed are:

1. ☒ 32 pages of specification, claims, abstract
2. ☒ 2 sheets of FORMAL drawing.
3. ☒ 2 pages of newly executed Declaration & Power of Attorney (copy).
4. ☒ Priority Claimed.
5. ☐ Small Entity Statement.
6. ☒ Information Disclosure Statement, Form PTO-1449 and reference.
7. ☒ Assignment Papers for LG Information & Communications, Ltd. (cover sheet, assignment & assignment fee).
8. ☒ Certified copy of Korean Patent Appln. No. 1999-14076, filed April 20, 1999.
9. ☒ Two (2) return postcards.
☒ Stamp & Return with Courier.
☒ Prepaid Postcard-Stamped Filing Date & Returned with Unofficial Serial Number.
10. ☒ Authorization under 37 C.F.R. §1.136(a)(3).
11. ☐ Other:

For	No. Filed		No. Extra	Rate	Fee
Total Claims	23	- 20	4	X \$18.00	\$ 54.00
Indep. Claims	4	- 3	1	X \$78.00	\$ 78.00
Multiple Dependent Claims (If applicable)				X \$260.00	
				BASIC FEE	\$690.00
				TOTAL FILING FEE	\$822.00

- ☐ This is a Continuation-in-part (CIP) of prior application No: _____ filed _____. Incorporation By Reference-The entire disclosure of the prior application is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.
- ☐ Amend the specification by inserting before the first line the sentence:
 -This application is a continuation-in-part of Application Serial No. _____ filed _____.-
- ☒ A check in the amount of \$ 822.00 (Check # 8612) is attached.
- ☐ Please charge my Deposit Account No. 16-0607 in the amount of \$ _____. A duplicate copy of this sheet is enclosed.
- ☒ The Commissioner is hereby authorized to charge payment of the following fees associated with this communication or credit any overpayment to Deposit Account No. 16-0607. A duplicate copy is enclosed.
- ☒ Any additional filing fees required under 37 C.F.R. 1.16.
- ☒ The Commissioner is hereby authorized to charge payment of following fees during the pendency of this application or credit any overpayment to Deposit Account No. 16-0607. A duplicate copy of this sheet is enclosed.
- ☒ Any patent application processing fees under 37 C.F.R. 1.17.
- ☒ Any filing fees under 37 C.F.R. 1.16 for presentation of extra claims.

FLESHNER & KIM, LLP

Anthony H. Nourse

Daniel Y.J. Kim
 Registration No. 36,186
 Anthony H. Nourse
 Registration No. 46,121

Correspondence Address Below:

P.O. Box 221200

Chantilly, VA 20153-1200

(703) 502-9440 DYK/AHN:jld

Date: April 19, 2000

Docket No.: K-164

PATENT

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of :
Sun Gil KIM and Sung Chul YANG :
Serial No.: To be assigned :
Filed: April 19, 2000 :



For: DEVICE FOR TRANSMISSION/RECEPTION OF FACSIMILE DATA
IN WIRELESS LOCAL LOOP (WLL) SYSTEM


AUTHORIZATION TO TREAT A REPLY AS INCORPORATING
AN EXTENSION OF TIME UNDER 37 C.F.R. §1.136(a)(3)

Assistant Commissioner for Patents
Washington, D. C. 20231

Sir:

The U.S. Patent and Trademark Office is hereby authorized to treat any concurrent or future reply that requires a petition for an extension of time under this paragraph for its timely submission, as incorporating a petition for extension of time for the appropriate length of time under 37 C.F.R. 1.136(a)(3). The U.S. Patent and Trademark Office is hereby authorized to charge all required extension of time fees to our Deposit Account No. 16-0607, if such fees are not otherwise provided for in such reply. A duplicate copy of this sheet is enclosed.

Respectfully submitted,
FLESHNER & KIM, LLP


Daniel Y.J. Kim
Registration No. 36,186
Anthony H. Nourse
Registration No. 46,121

P.O. Box 221200
Chantilly, VA 20153-1200
703 502-9440 DYK/AHN:jld
Date: April 19, 2000

APPLICATION FOR UNITED STATES LETTERS PATENT

INVENTORS: Sun Gil KIM and Sung Chul YANG

TITLE: DEVICE FOR TRANSMISSION/RECEPTION OF FACSIMILE
DATA IN WIRELESS LOCAL LOOP (WLL) SYSTEM

ATTORNEYS: The Law Offices of
& FLESHNER & KIM
ADDRESS: P. O. Box 221200
Chantilly, VA 20153-1200

DOCKET NO.: K-164

DEVICE FOR TRANSMISSION/RECEPTION OF FACSIMILE DATA IN WIRELESS LOCAL LOOP (WLL) SYSTEM

BACKGROUND OF THE INVENTION

1. Field of the Invention

5 The present invention relates to transmission/reception of a facsimile data in a Wireless Local Loop (WLL) system, and more particularly, to a device for transmission/reception of a facsimile data in a WLL system, in which an analog G3 facsimile signal is converted into a CDMA signal format for transmission/reception of the signal.

2. Background of the Related Art

10 In general, a Wireless Local Loop (WLL) system provides a wireless subscriber line between a switching center and homes or offices, for providing speech, facsimile, and data communication services. Full scale development of the WLL started as problems of frequency efficiency, radio channel quality, build up cost per a subscriber are solved when
15 the semiconductor and radio communication technologies developed in 1980s are combined with the radio frequency technology developed in 1970s.

Unlike a conventional wire network, the WLL system has the advantages of low build up cost and time, and low maintenance costs, while still providing a variety of services, such as excellent communication quality, data, and Integrated Service Digital

Network (ISDN) capabilities, and the like. Thus, the WLL system can be used where a new communication service provider intends to secure a subscriber network quickly, or used as a communication infrastructure of a developing country which has a poor wire communication network.

5 The WLL system is typically provided with telephone sets and a Network Interface Unit (NIU), which makes radio communication between the telephone sets and a switchboard possible. There are two types of WLL systems: the separate type WLL system and the integrated type WLL system. The separate WLL system is provided with a subscriber connector for wire connection to a stationary telephone so that the subscriber who has the stationary telephone set connected to an existing wire network can buy only the subscriber connector and not a telephone set when the subscriber subscribes to the WLL system. The integrated WLL system, on the other hand, is provided with the telephone set and the subscriber connector integrated in hardware for the convenience of the subscriber who has, for example, no stationary telephone set in subscription to the
15 WLL system.

 A related art Code Division Multiple Access (CDMA) WLL has a digital facsimile (class 2, 2.0) function for using a personal computer, with the personal computer connected to the NIU. However, since a group 3 (called G3 hereafter) facsimile signal is transmitted on a CDMA audio channel, a normal transmission/reception of the G3
20 facsimile is difficult. That is, the G3 facsimile transmission, which is a facsimile device

using a PSTN for transmission of an A4 size document within approximately one minute by compressing a number of bits to 1/10, has a problem when it is intended to transmit the facsimile data by using PCS or DCN in that normal facsimile data transmission/reception is extremely difficult because of distortion of the facsimile signal coming from difference between the PSTN and PCS or DCN transmission systems.

The above references are incorporated by reference herein where appropriate for appropriate teachings of additional or alternative details, features and/or technical background.

SUMMARY OF THE INVENTION

An object of the present invention is to overcome, in whole or in parts, one or more of the problems due to limitations and disadvantages of the related art.

Another object of the present invention is to provide a device for transmission/reception of a facsimile data in a WLL system, which permits facsimile data transmission and reception by using G3 facsimile device in a separate type WLL.

Additional features and advantages of the invention will be set forth in the description which follows, and in part will be apparent from the description, or may be learned by practice of the invention. The objectives and other advantages of the invention will be realized and attained by the structure particularly pointed out in the written description and claims hereof as well as the appended drawings.

To achieve these and other advantages and in accordance with the purpose of the present invention, as embodied and broadly described, the device for transmission/reception of a facsimile data in a separate type WLL system, includes an interface unit for transmitting a facsimile data produced at a facsimile or matching a data received in an analog facsimile protocol to wire line characteristics for providing the data to the facsimile, a facsimile signal processor for receiving the facsimile data from the interface unit, and converting into a digital signal and a radio data service format, or receiving a data in a radio data service format, converting into an analog facsimile protocol, and forwarding to the interface unit, a CDMA signal processor for receiving the facsimile data converted into the radio data service format from the facsimile signal processor and converting into a CDMA format, or receiving a data in a CDMA format, converting into the radio data format, and forwarding to the facsimile signal processor, and a frequency modulation /demodulation unit for frequency modulating the facsimile data converted into the CDMA format at the CDMA signal processor to forward in a radio signal, or receiving and demodulating an external radio signal, and forwarding to the CDMA signal processor.

In other aspect of the present invention, there is provided a device for transmission /reception of a facsimile data in a WLL system including an interface unit for transmitting the facsimile data generated at a facsimile, or matching a data received in a facsimile protocol to wire line characteristics for providing the data to the facsimile, a first CODEC

unit for converting a facsimile data signal from the interface unit into a digital signal, or converting a digital signal into the analog facsimile data signal, and forwarding to the interface unit, a second CODEC for converting a signal converted into the digital signal at the first CODEC unit into an analog signal, or converting an analog signal into a digital signal and forwarding to the first CODEC unit, a facsimile signal processor for receiving the analog facsimile data from the second CODEC, converting into a digital signal and a radio data service format and forwarding the converted signal, or receiving a data in a radio data service format, converting into an analog facsimile protocol, and forwarding to the second CODEC, a CDMA signal processor for receiving the facsimile data converted into the radio data service format from the facsimile signal processor and converting into a CDMA format, or receiving a data in a CDMA format, converting into the radio data service format, and forwarding to the facsimile signal processor, and a modulation/demodulation unit for frequency modulating the facsimile data converted into a CDMA format at the CDMA signal processor to forward in a radio signal, or receiving and demodulating an external radio signal, and forwarding to the CDMA signal processor.

The interface unit includes a jack for connecting the facsimile and an NIU, a ring generator for generating a ring signal if received at the facsimile, a detector for detecting and forwarding the facsimile data transmitted from the facsimile, and an Subscriber Line Integrated Circuit (SLIC) for receiving a signal detected at the detector, matching line

characteristics for transmission of the analog facsimile data generated at the facsimile, and transmitting the analog facsimile data to the facsimile signal processor.

The facsimile signal processor includes a DTMF receiver for receiving a Dual Tone Multi-Frequency (DTMF) generated at the facsimile, a first amplifier for amplifying and forwarding the analog facsimile signal from the interface unit, a modem for modulating and forwarding the analog facsimile signal amplified at the first amplifier, or demodulating and forwarding a modulated facsimile signal, a second amplifier for amplifying the analog facsimile signal demodulated at the modem, and forwarding to the interface unit, a first memory having a radio data service format(protocol, class 2, 2.0) used in a CDMA system and an analog facsimile protocol stored therein, a second memory for buffering the analog facsimile data signal and the radio data service format signal, and a controller for converting the analog facsimile signal demodulated at the modem into the radio data digital facsimile signal format used in a CDMA system, or converting the data converted into a radio data service format into the analog facsimile signal from the CDMA signal processor, both by using the first and the second memories, and forwarding to the modem.

In order to achieve at least the above-described objects of the present invention in a whole or in parts, there is provided a device for transmission/reception of facsimile data in a Wireless Local Loop (WLL) system that includes an interface unit, which transmits facsimile data produced at a facsimile or matches data received in an analog facsimile

protocol to wire line characteristics to provide the data to the facsimile, a facsimile signal processor, which receives the facsimile data from the interface unit, and converts the facsimile data into a digital signal with a radio data service format, or receives data in a radio data service format and converts it into an analog facsimile protocol to forward to the interface unit, a CDMA signal processor, which receives the radio data service formatted facsimile data from the facsimile signal processor and converts it into CDMA format, or receives data in CDMA format, converts it into the radio data format and forwards it to the facsimile signal processor, and a frequency modulation /demodulation unit, which frequency modulates the CDMA formatted facsimile data to forward as a radio signal, or receives and demodulates an external radio signal, and forwards the received signal to the CDMA signal processor.

To further achieve the above-described objects of the present invention in a whole or in parts, there is provided a device for transmission/reception of a facsimile data in a Wireless Local Loop (WLL) system that includes an interface unit, which transmits facsimile data generated at a facsimile, or matches data received in a facsimile protocol to wire line characteristics to provide to the facsimile, a first CODEC unit, which converts a facsimile data signal from the interface unit into a digital signal, or converts a received digital signal into an analog facsimile data signal to forward to the interface unit, a second CODEC unit, which converts the digital signal from the first CODEC unit into an analog signal, or converts an analog facsimile protocol signal into the received digital

signal to forward to the first CODEC unit, a facsimile signal processor, which receives the analog signal from the second CODEC unit and converts it into a digital signal having a radio data service format, or which receives data in a radio data service format, converts it into the analog facsimile protocol signal, and forwards it to the second CODEC unit, a CDMA signal processor, which receives the digital signal having the radio data service format from the facsimile signal processor and converts it into a CDMA format, or which receives data in a CDMA format, converts it into the radio data service format, and forwards it to the facsimile signal processor, and a modulation/demodulation unit, which modulates the CDMA formatted signal received from the CDMA signal processor, or which receives and demodulates an external radio signal to forward to the CDMA signal processor.

To further achieve the above-described objects of the present invention in a whole or in parts, there is provided a signal processing device that includes an interface unit to couple with at least one input device and detect and receive a device signal or output a device signal, a signal processor coupled to receive an interface signal and convert a data format of the signal or provide an interface signal to the interface unit, a Code Division Multiple Access (CDMA) signal processor coupled to receive a processed signal from the signal processor and generate a CDMA formatted signal.

To further achieve the above-described objects of the present invention in a whole or in parts, there is provided a method for transmitting facsimile data that includes

detecting analog facsimile data from a facsimile, providing a detection signal to a controller and a Subscriber Line Integrated Circuit (SLIC), matching line characteristics and the SLIC according to the detection signal, transmitting the analog facsimile signal to a modem through a first amplifier, modulating the analog facsimile signal and forwarding it to the controller, converting the analog facsimile signal to a digital signal using a prescribed protocol, forwarding the digital signal to a CDMA signal processor, converting the digital signal into a CDMA protocol, and modulating the CDMA protocol digital signal.

Additional advantages, objects, and features of the invention will be set forth in part in the description which follows and in part will become apparent to those having ordinary skill in the art upon examination of the following or may be learned from practice of the invention. The objects and advantages of the invention may be realized and attained as particularly pointed out in the appended claims.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will be described in detail with reference to the following drawings in which like reference numerals refer to like elements wherein:

Figure 1 is a drawing which illustrates a block diagram of a device for transmission/reception of a facsimile data in a WLL system in accordance with a first preferred embodiment of the present invention; and,

Figure 2 is a drawing which illustrates a block diagram of a device for transmission/reception of a facsimile data in a WLL system in accordance with a second preferred embodiment of the present invention.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

5 Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings.

Referring to Figure 1, the device for transmission/reception of a facsimile data in a WLL system in accordance with a first preferred embodiment of the present invention preferably includes a facsimile unit 20 used, for example, in a home or an office, and an interface unit 100 for transmitting facsimile data produced at the facsimile 20, or matching data received in an analog facsimile protocol to wire line characteristics for transmission to the facsimile 20. The system further includes a facsimile signal processor 200 for receiving the facsimile data from the interface unit 100 and converting it into a digital signal and a radio data service format (for example, converting an analog facsimile data protocol into a facsimile service protocol (class 2, 2.0) used in a CDMA system), or receiving data in a radio data service format, converting it into an analog facsimile protocol, and forwarding it to the interface unit 100.

Next, a CDMA signal processor 300, for example, a mobile station modem, is provided for receiving the facsimile data converted into the radio data service format from

the facsimile signal processor 200 and converting it into a CDMA format, or receiving data in CDMA format, converting it into the radio data format, and forwarding it to the facsimile signal processor. The system also includes a frequency modulation /demodulation unit 400 for frequency modulating facsimile data converted into CDMA
5 format at the CDMA signal processor 300, to forward it as a radio signal, or receiving and demodulating an external radio signal, and forwarding it to the CDMA signal processor 300.

The interface unit 100 includes a jack 22 for connecting the facsimile 20 and an NIU, a ring generator 24 for generating a ring signal if a call is received at the facsimile 20, and a detector 18 for detecting facsimile data transmitted from the facsimile 20. It further includes a Subscriber Line Integrated Circuit (SLIC) 25 for receiving a signal detected at the detector 18, matching line characteristics, and transmitting the analog facsimile data produced at the facsimile 20 to the facsimile signal processor 200.

The facsimile signal processor 200 includes a DTMF receiver 19 for receiving a
15 Dual Tone Multi-Frequency (DTMF) signal generated at the facsimile 20, a first amplifier 13a for amplifying and forwarding the analog facsimile signal from the interface unit 100, and a modem 14 for modulating and forwarding the analog facsimile signal amplified at the first amplifier 13a, or demodulating and forwarding a modulated facsimile signal. It further includes a second amplifier 13b for amplifying the analog facsimile signal
20 demodulated at the modem 14 and forwarding it to the interface unit 100, and a first

memory 15 having a radio data service format (protocol, class 2, 2.0) used in a CDMA system and an analog facsimile protocol stored therein. A second memory 16 buffers the analog facsimile data signal and the CDMA digital facsimile data format signal. A controller 11 converts the analog facsimile signal demodulated at the modem into the radio data digital facsimile signal format (class 2, 2.0) used in a CDMA system, or converts the data converted into a digital facsimile signal format into the analog facsimile signal, both by using the first and the second memories 15 and 16. It then forwards the result to the interface unit 100 through the modem 14 and the second amplifier 13b. Switch 17 is also included.

The operation of the device for transmission/reception of a facsimile data in a WLL in accordance with a first preferred embodiment of the present invention will now be described.

When the facsimile 20 transmits facsimile data, the detector 18 detects the facsimile data and provides a detection signal to the controller 11 and the SLIC 25. The SLIC 25 matches line characteristics according to the detection signal from the detector 18 to transmit the facsimile data generated at the facsimile 20 to the facsimile signal processor 200. The first amplifier 13a in the facsimile signal processor 200 amplifies the facsimile data transmitted from the SLIC 25 in the interface unit 100 and forwards it to the modem 14. The modem 14 receives and modulates the analog facsimile signal and forwards it to the controller 11.

The controller 11 preferably uses the first and second memories 15 and 16 to convert the protocol of the analog facsimile signal received from the modem 14 into the radio data service format/protocol (class 2, 2.0), and forwards the converted signal to the CDMA signal processor 300. The CDMA signal processor 300 receives the facsimile data
5 in the radio data service format (facsimile service protocol, class 2, 2.0) from the facsimile signal processor 200, converts it into a CDMA format, and forwards it to the modulation /demodulation unit 400. The modulation/demodulation unit 400 frequency modulates the facsimile data converted into the CDMA format at the CDMA signal processor 300 into a radio signal.

Next, a method for receiving the facsimile data will be described. The modulation/demodulation unit 400 demodulates an external radio signal and forwards it to the CDMA signal processor 300 in CDMA format. The CDMA signal processor 300 receives the data in CDMA format and converts the data into a radio data service format, and then forwards it to the facsimile signal processor 200. The facsimile signal processor
15 200 receives the data in the radio data service format (class 2, 2.0) from the CDMA signal processor 300 through the controller 11. It then uses the first and second memories 15 and 16 to convert the data into the analog facsimile protocol, demodulates and amplifies it through the modem 14 and the second amplifier unit 13b, and forwards it to the interface unit 100. The facsimile 20 thus receives a facsimile signal through the interface unit 100.

Figure 2 illustrates a block diagram of a device for transmission/reception of facsimile data in a WLL system according to a second preferred embodiment of the present invention, which permits one to use a domestic telephone set, computer, and facsimile.

5 Referring to Figure 2, the device for transmission/reception of facsimile data in a WLL system preferably includes a facsimile unit 20 which can be used, for example, in a home or an office, and an interface unit 100 for transmitting facsimile data generated at the facsimile 20. The device also includes a wire telephone set 30, a computer 40, for matching data received in facsimile protocol to wire line characteristics so as to provide the data to the facsimile 20.

Next, a first CODEC unit 500 converts speech or an analog facsimile data signal from the interface unit 100 into a digital signal, or converts a digital signal into speech or an analog facsimile data signal. It then forwards the signal to the interface unit 100. A second CODEC unit 600 converts the signal converted into the digital signal at the first
15 CODEC unit 500 into an analog signal, or converts the analog signal into a digital signal, which it then forwards to the first CODEC unit 500.

The device further includes a facsimile signal processor 200 for receiving the analog facsimile data from the second CODEC unit 600, converting it into a digital signal and a radio data service format (class 2, 2.0), and forwarding the converted signal.
20 Alternatively, the facsimile signal processor 200 receives data in a radio data service

format, converts it into an analog facsimile protocol, and forwards it to the second CODEC 600.

Next, a switching unit 700 switches the computer 40 between the facsimile signal processor 200 and the CDMA signal processor 300. The CDMA signal processor 300 receives the facsimile data converted into the radio data service format from the facsimile signal processor 200 through the switching unit 700 and converts it into a CDMA format. Alternatively, it receives data in a CDMA format, converts it into the radio data format, and forwards it to the facsimile signal processor 200 through the switching unit 700.

The device next includes a modulation /demodulation unit 400 for frequency modulating the facsimile data converted into CDMA format at the CDMA signal processor 300 to forward as a radio signal, or receiving and demodulating an external radio signal, and forwarding it to the CDMA signal processor 300.

The interface unit 100 includes first and second jacks 21 and 22 for connecting the facsimile 20 and the wire telephone set 30 to a NIU, and a ring generator 24 for generating a ring signal if a call is received at the facsimile 20 or the wire telephone set 30. Next, a detector 18 detects and forwards facsimile data transmitted from the facsimile 20, and SLIC 25 holds the use of the facsimile 20 if a call is received at the wire telephone set 30. The SLIC 25 further receives a signal detected at the detector 18, matches line characteristics, and transmits the analog facsimile data produced at the facsimile 20 to the facsimile signal processor 200.

The first CODEC unit 500 includes a first DTMF receiver 27 for receiving a DTMF signal generated at the wire telephone set 30 or the facsimile 20 through the interface unit 100, and forwarding the signal to the CDMA signal processor 300. The unit also includes a first CODEC 26 for receiving the facsimile data from the interface unit 100 and converting it into digital data, or receiving digital data from the second CODEC unit 600, converting it into an analog signal, and forwarding it to the interface unit 100.

The term CODEC is a compound word of "CODER," for converting an analog signal into a digital signal, and conversely, "DECODER," for converting a digital signal into an analog signal, and denotes a modulation/demodulation unit or a code decoder. In general, coding is an operation in which an information source of a continuous signal is transformed (sampled) into a time basis discrete Pulse Amplitude Modulation (PAM) signal, and quantized. This allows the continuous signal to be converted into a binary code ('1' or '0'). An operation in reverse of the foregoing operation is called decoding.

In order to transmit an electric signal as information carried in a network through a digital transmission line or a digital switchboard, which are more economical, an analog signal is preferably converted into a digital signal before transmission or exchange. Thus, the signal is expressed in "1" and "0". Thereafter, the transmitted digital signal should be converted into the original analog signal at the receiver side. Such an operation is called as "coding/decoding" or "analog/digital conversion," or "digital/analog conversion." A device for such conversion is called CODEC.

1 The facsimile signal processor 200 includes a DTMF receiver 19 for receiving a
DTMF generated at the facsimile 20, a first amplifier 13a for amplifying and forwarding
the analog facsimile signal from the second CODEC unit 600, and a modem 14 for
modulating and forwarding the analog facsimile signal amplified at the first amplifier 13a,
5 or demodulating and forwarding a modulated facsimile signal. It further includes a second
amplifier 13b for amplifying the analog facsimile signal demodulated at the modem 14,
and forwarding it to the second CODEC unit 600.

10 The facsimile signal processor 200 also includes a first memory 15, having a radio
data service format (protocol, class 2, 2.0) used in a CDMA system and an analog facsimile
signal protocol stored therein, and a second memory 16 for buffering the analog facsimile
data signal and the CDMA digital facsimile data format signal. Next, and a controller 11
converts the analog facsimile signal from the modem 14 into the radio data digital
facsimile signal format (class 2, 2.0) used in a CDMA system, or receives data in a radio
data format from the CDMA signal processor 300 and converts the data into the analog
15 facsimile protocol signal. Both conversions of the controller 11 are preferably done by
using the first and the second memories 15 and 16. The signal is then forwarded to the
second CODEC unit 600 through the modem 14 and the second amplifier 13b. The
system also contains a switch 17.

20 An operation of the device for transmission/reception of facsimile data in a WLL
in accordance with a second preferred embodiment of the present invention will be

described. A first hook signal hook 1 is generated at the SLIC 25 and is a hook signal for the wire telephone set 30, and a second hook signal hook 2 is generated at the CDMA signal processor 300, and is a hook signal for the facsimile. The G3 facsimile transmission is made at the facsimile 20 by using a radio link through the CDMA signal processor 300.

5 When the facsimile 20 transmits facsimile data, the detector 18 detects the facsimile data and provides a detection signal to the controller 11 and the SLIC 25. The SLIC 25 matches line characteristics according to the detection signal from the detector 18 to transmit the facsimile data generated at the facsimile 20 to the first CODEC 26 through the first switch 17 and the SLIC 25. The first CODEC 26 converts the facsimile data into a digital signal and forwards it to the second CODEC 12. The second CODEC 12 then converts the digital signal into an analog signal again, and transmits it to the facsimile signal processor 200. The first amplifier 13a in the facsimile signal processor 200 amplifies the facsimile data transmitted from the second CODEC 12 and forwards it to the modem 14. The modem 14 receives and modulates the analog facsimile signal and forwards it to
15 the controller 11.

 The controller 11 preferably uses the first and second memories 15 and 16 to convert the protocol of the analog facsimile signal received from the modem 14 into the radio data service format/protocol (class 2, 2.0), and forwards it to the CDMA signal processor 300 through the switching unit 700. The CDMA signal processor 300 receives
20 the facsimile data in the radio data service format (facsimile service protocol, class 2, 2.0)

from the facsimile signal processor 200, converts it into a CDMA format, and forwards it to the modulation/demodulation unit 400. The modulation/demodulation unit 400 then modulates the CDMA formatted facsimile data into a radio signal.

When receiving facsimile data, the modulation/demodulation unit 400 demodulates an external radio signal and forwards the radio signal to the CDMA signal processor 300 in CDMA format. The CDMA signal processor 300 receives the CDMA formatted data and converts the data into a radio data service format, and forwards it to the facsimile signal processor 200 through the switching unit 700. The facsimile signal processor 200 receives the radio data service formatted data from the CDMA signal processor 300 through the controller 11, and preferably uses the first and second memories 15 and 16 to convert the data into the analog facsimile protocol. The facsimile signal processor 200 then amplifies the signal through the modem 14 and the second amplifier unit 13b, and forwards it to the second CODEC unit 600. That is, the controller 11 receives the data in the radio data service format (class 2, 2.0), buffers it at the second memory 16, and uses the analog facsimile protocol stored in the first memory 15 to convert the data into the analog facsimile signal format.

The analog formatted facsimile signal format is demodulated, amplified, and converted into a digital signal as the facsimile signal passes through the modem 14, the second amplifier 13b, and the second CODEC 12. The signal is then forwarded to the first CODEC 26. The first CODEC 26 converts the digital facsimile signal into the

analog facsimile signal and forwards it to the facsimile 20 through the interface unit 100.

The facsimile 20 receives and forwards the analog facsimile signal format data.

As has been explained, the device for transmission/reception of a facsimile data in a WLL system has several advantages. For example, the transmission of analog data, not directly through a voice channel, but after the analog data is converted into a CDMA digital facsimile data format by providing hardware which can convert the analog data into a radio data service format (class 2, 2.0) permits the transmission/reception of an analog facsimile data connected to NIU in a WLL by using a CDMA system.

The foregoing embodiments and advantages are merely exemplary and are not to be construed as limiting the present invention. The present teaching can be readily applied to other types of apparatuses. The description of the present invention is intended to be illustrative, and not to limit the scope of the claims. Many alternatives, modifications, and variations will be apparent to those skilled in the art. In the claims, means-plus-function clauses are intended to cover the structures described herein as performing the recited function and not only structural equivalents but also equivalent structures.

WHAT IS CLAIMED IS:

1. A device for transmission/reception of facsimile data in a Wireless Local Loop (WLL) system, comprising:

an interface unit, which transmits facsimile data produced at a facsimile or matches data received in an analog facsimile protocol to wire line characteristics to provide the data to the facsimile;

a facsimile signal processor, which receives the facsimile data from the interface unit, and converts the facsimile data into a digital signal with a radio data service format, or receives data in a radio data service format and converts it into an analog facsimile protocol to forward to the interface unit;

a CDMA signal processor, which receives the radio data service formatted facsimile data from the facsimile signal processor and converts it into CDMA format, or receives data in CDMA format, converts it into the radio data format and forwards it to the facsimile signal processor; and

a frequency modulation /demodulation unit, which frequency modulates the CDMA formatted facsimile data to forward as a radio signal, or receives and demodulates an external radio signal, and forwards the received signal to the CDMA signal processor.

2. The device of claim 1, wherein the interface unit comprises:

a jack to connect the facsimile and a Network Interface Unit (NIU);

a ring generator to generate a ring signal if a call is received for the facsimile;

a detector to detect and forward the facsimile data transmitted from the

5 facsimile; and

an Subscriber Line Integrated Circuit (SLIC) to receive a signal detected at the detector, match line characteristics for transmission of the analog facsimile data generated at the facsimile, and transmit the analog facsimile data to the facsimile signal processor.

3. The device of claim 1, wherein the facsimile signal processor comprises:

a Dual Tone Multi-Frequency (DTMF) receiver to receive a DTMF generated by the facsimile;

a first amplifier to amplify and forward the analog facsimile signal from the interface unit;

a modem to modulate and forward the analog facsimile signal amplified at the first amplifier, or demodulate and forward a modulated facsimile signal;

a second amplifier to amplify the facsimile signal demodulated at the modem, and forward it to the interface unit;

10 a first memory to store a radio data service format and an analog facsimile protocol;

a second memory to buffer the analog facsimile data signal and the radio data service formatted signal; and

15 a controller coupled to the first and second memories to convert the analog facsimile signal received from the modem into a radio data service format, or convert a radio data service format data from the CDMA signal processor into the analog facsimile signal to forward to the modem.

4. The device of claim 1, wherein the radio data service format includes a facsimile service protocol, class 2, 2.0.

5. A device for transmission/reception of a facsimile data in a Wireless Local Loop (WLL) system, comprising:

5 an interface unit, which transmits facsimile data generated at a facsimile, or matches data received in a facsimile protocol to wire line characteristics to provide to the facsimile;

a first CODEC unit, which converts a facsimile data signal from the interface unit into a digital signal, or converts a received digital signal into an analog facsimile data signal to forward to the interface unit;

a second CODEC unit, which converts the digital signal from the first
10 CODEC unit into an analog signal, or converts an analog facsimile protocol signal into
the received digital signal to forward to the first CODEC unit;

a facsimile signal processor, which receives the analog signal from the second
CODEC unit and converts it into a digital signal having a radio data service format, or
which receives data in a radio data service format, converts it into the analog facsimile
15 protocol signal, and forwards it to the second CODEC unit;

a CDMA signal processor, which receives the digital signal having the radio
data service format from the facsimile signal processor and converts it into a CDMA
format, or which receives data in a CDMA format, converts it into the radio data service
format, and forwards it to the facsimile signal processor; and

a modulation/demodulation unit, which modulates the CDMA formatted
signal received from the CDMA signal processor, or which receives and demodulates an
external radio signal to forward to the CDMA signal processor.

6. The device of claim 5, wherein the interface unit comprises:

first and second jacks to connect at least one of the facsimile and a wire
telephone set to a Network Interface Unit;

a ring generator to generate a ring signal if a call is received at the facsimile
5 or the wire telephone set;

a detector to detect and forward the facsimile data produced at the facsimile;
and

a Subscriber Line Integrated Circuit to receive a signal detected at the detector, match line characteristics, transmit the facsimile data generated at the facsimile
10 to the first CODEC unit or prevent the use of the facsimile if a call is received at the wire telephone set.

7. The device of claim 5, wherein the first CODEC unit comprises:

a first DTMF receiver to receive through the interface unit a DTMF signal generated at one of the wire telephone set and the facsimile and forward it to the CDMA signal processor; and

a first CODEC to receive the facsimile data from the interface unit and
5 convert it into digital data, or receive digital data from the second CODEC unit, convert it into an analog signal, and forward it to the interface unit.

8. The device of claim 5, further comprising a switching unit, which selects one of a computer and the facsimile signal processor to couple to the CDMA signal processor.

9. The device of claim 8, wherein the switching unit comprises:
a connecting unit to connect the computer to a Network Interface Unit;
first and second control circuits to control data transmission and reception
between the CDMA signal processor and the computer, and
5 a switching circuit to couple one of the facsimile signal processor and the
computer to the CDMA signal processor according to the data communication.

10. A signal processing device, comprising:
an interface unit to couple with at least one input device and detect and
receive a device signal or output a device signal;
a signal processor coupled to receive an interface signal and convert a data
format of the signal or provide an interface signal to the interface unit;
5 a Code Division Multiple Access (CDMA) signal processor coupled to
receive a processed signal from the signal processor and generate a CDMA formatted
signal or receive a CDMA formatted signal and output a radio data formatted signal to the
signal processor.

11. The device of claim 10, further comprising a modulating and demodulating
unit communicatively coupled to the CDMA signal processor to receive or provide a
CDMA formatted signal.

12. The device of claim 10, wherein the signal processor comprises:

a Dual Tone Multi-Frequency (DTMF) receiver coupled to receive a control signal from the interface unit;

an amplifier communicatively coupled to the interface unit;

a modem communicatively coupled to the amplifier; and

a controller communicatively coupled to the modem and the CDMA signal processor, wherein the modem receives an amplified interface signal and generates a modulated interface signal, or receives a modulated signal from the controller to generate a demodulated signal as the interface signal.

13. The device of claim 12, wherein the controller further comprises:

a first memory device;

a second memory; and

a central processing unit, wherein the first memory device stores a prescribed protocol, the second memory unit buffers a signal to be converted by the controller, and the CPU converts a format of the data stored in the second memory according to the protocol stored in the first memory.

14. The device of claim 10, further comprising:

a CODEC device communicatively coupled to the interface unit and the signal processor; and

a switching unit to selectively couple the CDMA signal processor to one of the signal processor and a computer.

15. The device of claim 14, wherein the CODEC device comprises:

a first CODEC unit communicatively coupled to the interface unit; and

a second CODEC unit communicatively coupled to the first CODEC unit and the signal processor, wherein the first CODEC unit converts a signal received from the interface unit from a first format to a second format and converts a signal received from the second CODEC unit from the second format into the first format, and wherein the second CODEC unit converts a signal received from the first CODEC unit from the second format into a third format, and converts a signal received from the signal processor from the third format into the second format.

16. The device of claim 15, wherein the first and third formats are an analog format, and the second format is a digital format.

17. The device of claim 15, wherein the switching unit comprises:

first and second control circuits for controlling data transmission and reception between the CDMA signal processor and a computer, and

a switching circuit to selectively couple the CDMA signal processor to one
5 of the signal processor and the computer.

18. The device of claim 17, wherein the switching unit further comprises a network interface unit coupled to the computer and each of the first and second control circuits.

19. The device of claim 17, wherein the signal processor comprises:

a controller coupled to the first and second memories to convert the modulated interface signal received from the modem into a radio data service format, or convert a radio data service format data signal from the CDMA signal processor into the
5 modulated interface signal, and forward it to the modem

a second DTMF receiver coupled to receive a control signal from the interface unit;

a modem to modulate and forward the output of the second CODEC unit and demodulate and forward data to the second CODEC;

10 an amplifier for amplifying the signals to and from the modulator;

a memory to store a radio data service format and an analog facsimile protocol and to buffer signals to be converted by the controller.

20. The device of claim 19, where in the interface unit comprises:
first and second jacks to couple to first and second input devices;
a ring generator to generate a ring signal if a call is received at the first or second input device;
a detector to detect and forward data from the second input device; and
a Subscriber Line Integrated Circuit to receive data from the detector, match line characteristics, and transmit the data to the first CODEC unit.

21. The device of claim 20, wherein the first input device is a wire telephone set and the second input device is a facsimile.

22. The device of claim 10, wherein the signal processor receives an analog facsimile signal and converts it to a digital radio data service format.

23. A method for transmitting facsimile data, comprising:
- detecting analog facsimile data from a facsimile;
 - providing a detection signal to a controller and a Subscriber Line Integrated Circuit (SLIC);
 - 5 matching line characteristics and the SLIC according to the detection signal;
 - transmitting the analog facsimile signal to a modem through a first amplifier;
 - modulating the analog facsimile signal and forwarding it to the controller;
 - converting the analog facsimile signal to a digital signal using a prescribed protocol;
 - forwarding the digital signal to a CDMA signal processor;
 - converting the digital signal into a CDMA protocol; and
 - modulating the CDMA protocol digital signal.

ABSTRACT OF THE DISCLOSURE

A device for transmission/reception of a facsimile data in a separate type WLL system is provided, in which an analog G3 facsimile signal is converted into a CDMA signal format for transmission/reception of the signal. The device includes an interface unit for transmitting facsimile data produced at a facsimile, or matching data received in an analog facsimile protocol to wire line characteristics for providing the data to the facsimile, a facsimile signal processor for receiving the facsimile data from the interface unit and converting it into a digital signal and a radio data service format, or receiving a data in a radio data service format, converting it into an analog facsimile protocol, and forwarding it to the interface unit. It also includes a CDMA signal processor for receiving the converted facsimile data from the facsimile signal processor and converting it into a CDMA format, or receiving data in a CDMA format, converting into the radio data format, and forwarding it to the facsimile signal processor. It also includes a frequency modulation/demodulation unit for frequency modulating the CDMA formatted facsimile data, or receiving and demodulating an external radio signal, and forwarding it to the CDMA signal processor.

FIG.1





FIG.2



Docket No.: **K-164****DECLARATION AND POWER OF ATTORNEY**

As a below named inventor, I hereby declare that:

My residence, post office and citizenship are as stated below next to my name,

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter claimed and for which a patent is sought on the invention entitled **DEVICE FOR TRANSMISSION/RECEPTION OF FACSIMILE DATA IN WIRELESS LOCAL LOOP (WLL) SYSTEM**, the specification of which

[X] is attached hereto [] was filed on _____ as Application Serial No. _____ and was amended on _____ (if applicable)

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is known to me to be material to patentability in accordance with Title 37, Code of Federal Regulations, Section 1.56(a).

I hereby claim foreign priority benefits under 35 U.S.C. 119(a)-(d) or 365 (b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or of any PCT international application having a filing date before that of the application on which priority is claimed.

Prior Foreign Application(s):**Number****Country****Foreign Filing Date****Month/Day/Year**

1999-14076 Republic of Korea April 20, 1999

I hereby claim the benefit under 35 U.S.C. 119(e) of any United States provisional application(s) listed below.

Application Number(s):**Filing Date (Month/Day/Year)**

I hereby claim the benefit under 35 U.S.C. 120 of any United States application(s), or 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT international application in the manner provided by the first paragraph of 35 U.S.C. 112, I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

**Prior U. S. Application
or PCT Parent Number**

Filing Date (Month/Day/Year)**Parent Patent Number (if applicable)**

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so

made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

I hereby appoint the following attorney(s) and/or agent(s): Daniel Y.J. Kim, Registration No. 36,186 and Mark L. Fleshner, Registration No. 34,596; Carl R. Wesolowski, Registration No. 40,372, John C. Eisenhart, Registration No. 38,128, Rene A. Vazquez, Registration No. 38,647; Michael J. Cornelison, Registration No. 40,395; Stuart I. Smith, Registration No. 42,159; and Carol L. Druzbeck, Registration No. 40,287; and Anthony H. Nourse, Registration No. 46,121, all of

FLESHNER & KIM, LLP
P. O. Box 221200
Chantilly, Virginia 20153-1200

with full power of substitution and revocation, to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith, and all future correspondence should be addressed to them.

Full name of sole or first inventor: Sun Gil KIM

Inventor's signature: Simon J. Kim

Date: 12 APR 2000

Residence: Kyonggi-do, Korea

Citizenship: Republic of Korea

Post Office Address: Aju 1cha APT., 101-112, 1135, Chisan-dong, Pyongtaek-shi, Kyonggi-do, Korea

Full name of joint inventor(s): Sung Chul YANG

Inventor's signature: Sung Chul Yang

Date: 12 Apr, 2000

Residence: Kyonggi-do, Korea

Citizenship: Republic of Korea

Post Office Address: Kochung Jukong APT., 107-1507, Haan2-dong, Kwangmyong-shi, Kyonggi-do, Korea

Full name of joint inventor(s):

Inventor's signature:

Date:

Residence:

Citizenship:

Post Office Address: